Medical Oxygen Generators Standard Series

The Premium Performance

Oxywise Oxygen generators produce high quality oxygen from compressed air by Pressure Swing Adsorption (PSA). Our generators represent a reliable and cost effective alternative to traditional Oxygen supplies.



Standard Features

- Colour touch screen control
- Built in purity analyzer for constant monitoring
- Data-logging via USB interface
- Modbus TCP. Ethernet connection
- Remote start/stop relay
- Stainless steel piping
- Designed for dynamic pressure loading
- Purity control off spec purge
- Audio-visual alarm

Optional add-ons

- ✓ Flow control valve flow & purity adjustment
- Energy saving valve reduces compressed air usage during turn down
- Sequential start/stop one button operation
- SMS alarm
- Remote monitoring
- and others





Medical Oxygen Generators Standard Series

Model	Oxygen capacity						Dimensions	Weight
	90%		93%		95%		LxWxH	
	kg/h	m³/h	kg/h	m³/h	kg/h	m³/h	cm	kg
O2	1.6	1.2	1.5	1.1	1.4	1.1	62x70x170	165
04	3.4	2.6	3.2	2.4	2.9	2.2	65x75x195	200
O6	4.2	3.2	3.9	2.9	3.5	2.6	65x80x195	250
O9	5.8	4.4	5.4	4.1	4.9	3.7	78x82x195	350
O12	8.2	6.2	7.7	5.8	6.9	5.2	82x82x212	450
O15	11.2	8.4	10.5	7.9	9.5	7.1	87x83x213	550

Operating conditions

5°C to 50°C
4 - 6 bargG
-50°C (-70°C)
7.5 to 10 barG
ISO: 8573.1:2010 class 1.4.1.
3°C
0.01 micron
110-240V / 50-60Hz

Notes

Performance data is based on 7 barG inlet pressure and 20°C to 30°C ambient temperature.

Flow stated in cubic meter (m3) is with reference conditions, Temperature: 20°C, Pressure: 1.013 barA.

Conversion factor for m3 with reference conditions, Temperature: 0°C, Pressure: 1.013 barA is 0.69 m3/kg.

Designs and specifications are subject to change without notice or obligation.

Installation alternatives

- generating system including air treatment
- stand-alone installation
- skid mounted variant
- containerized version
- oxygen generating system with cylinder filling station
- partial filling station

KEY Benefits

- Flexibility
- Cost effective
- Safety
- Easy operation
- Reliability



